

Product Specifications

Beta® 87A Supercardioid Condenser Vocal Microphone

Overview

The Shure Beta 87A is a precision-engineered supercardioid condenser vocal microphone with an exceptionally smooth frequency response. Built to withstand extreme sound pressure levels, the Beta 87A is ideal for professional sound reinforcement and studio recording applications - and constructed to withstand the rigors of touring.

Features

- Premier live performance microphone with Shure quality, ruggedness, and reliability
- Uniform supercardioid pick-up pattern for maximum gain before feedback and superior rejection of off-axis sound
- Smooth, wide frequency response with gradual presence rise and controlled proximity effect tailored for vocals
- Advanced cartridge shock mount system absorbs mechanical shock and minimizes handling noise
- Dent-resistant steel mesh grille and enamel coated metal alloy construction resist wear and abuse
- Effective built-in pop filter reduces undesirable wind and breath noise
- Very low susceptibility to RF and electromagnetic hum

Available Models

Beta 87A	Supercardioid Condenser Vocal Microphone
-----------------	--



Beta 87A


Specifications

Cartridge Type	Electret Condenser
Frequency Response	20 to 20,000 Hz
Polar Pattern	Supercardioid
Output Impedance	150 Ω
Sensitivity <i>(at 1 kHz, open circuit voltage)</i>	-52.5 dBV/Pa (2 mV) 1 Pascal=94 dB SPL
Maximum SPL <i>(1 kHz at 1% THD, 1kΩ load)</i>	140.5 dB
Signal-to-Noise Ratio <i>(referenced at 94 dB SPL at 1 kHz)</i>	70.5 dB <i>S/N ratio is difference between 94 dB SPL and equivalent SPL of self noise, A-weighted</i>
Dynamic Range <i>(at 1 kHz, 1 kΩ load)</i>	117 dB
Clipping Level <i>(1 kHz at 0.25% THD, 1kΩ load)</i>	-6 dBV (0.5 V)
Self Noise <i>(typical, equivalent SPL, A-weighted)</i>	23.5 dB typical
Polarity	Positive pressure on diaphragm produces positive voltage on pin 2 with respect to pin 3
Weight	Net: 0.207 kg (0.475 lbs)
Connector	Three-pin professional audio (XLR), male
Power Requirements	11 to 52 Vdc phantom (1.2 mA)


Accessories and Replacement Parts

RK312	Replacement grille	RK193	Replacement cartridge
A85WS	Microphone windscreen	A25D	Microphone clip

Polar Pattern



Frequency Response



SHURE[®]
LEGENDARY
PERFORMANCE™

www.shure.com

©2015 Shure Incorporated