

SHURE®

LEGENDARY
PERFORMANCE™

DIS Digital Conference Systems

BP 6001 Battery Pack

BP 6001 Battery Pack

- Battery pack for DIS digital IR receivers
- Rechargeable
- Temperature sensor to optimize the charging process



Description

The BP 6001 Battery Pack is designed for use with the DIS Digital IR Receivers. It provides up to 75 hours of use for the DR 60xx units. The battery pack replaces the two AA size alkaline batteries if rechargeable function is needed.

The CT 6056 Charging Tray is used for recharging up to 56 batteries at once.

Features

The BP 6001 has the following standard features:

- Supplies power for the DR 60xx digital receiver units
- NiMH type rechargeable
- 1100 mAh
- Temperature sensor for optimal charging process

Specifications

Interconnections

Connector	Battery contact
------------------	-----------------

Electrical

Voltage	2.4 V
----------------	-------

Capacity	1100 mAh
-----------------	----------

Mechanical

Dimensions	14 x 28 x 49 mm (W x H x D)
-------------------	-----------------------------

Net Weight	50 g
-------------------	------

Color	Black
--------------	-------

Temperature range	• Transport: -40 to +70° C (-40 - 158° F) • Operating: 5 to 45° C (41 to 113° F)
--------------------------	---

Certifications

The DCS 6000 system conforms to standard IEC 60914.

How To Order

Rechargeable Battery Pack for Digital Receivers 60xx **BP 6001**

SHURE[®]
LEGENDARY
PERFORMANCE™

United States, Canada,
Latin America, Caribbean:
Shure Incorporated
5800 West Touhy Avenue
Niles, IL 60714-4608 USA

Phone: +1 847-600-2000
Fax: +1 847-600-1212 (USA)
Fax: +1 847-600-6446
Email: info@shure.com
www.shure.com

Europe, Middle East, Africa:
Shure Europe GmbH
Jakob-Dieffenbacher-Str. 12,
75031 Eppingen, Germany

Phone: +49-7262-92490
Fax: +49-7262-9249114
Email: info@shure.de
www.shure.eu

Asia, Pacific:
Shure Asia Limited
22/F, 625 King's Road
North Point, Island East
Hong Kong

Phone: +852-2893-4290
Fax: +852-2893-4055
Email: info@shure.com.hk
www.shureasia.com