

Shure Performance Gear VHF and T Series Wireless Frequency Compatibility Chart (169.445-208.200 MHz)

Shure Performance Gear VHF and T Series Wireless Systems in the United States are available in 8 frequencies between 176.200 MHz and 208.200 MHz, plus 2 traveling frequencies (169.445 MHz & 171.845 MHz). Up to 6 Shure Performance Gear VHF and T Series Wireless Systems can be operated simultaneously in a single location. Frequencies within a given broadcast TV channel are compatible. Contact Shure Incorporated if you need additional information or assistance in frequency selection and setup.

If TV Channels 8, 10 or 12 are present/occupied, use the following frequency codes. (All are compatible)

Performance Gear VHF and T Series Code/Frequency "Blue Dot Group"			This frequency is in US TV Channel:
CA	176.200	MHz	TV 7
CC	177.600	MHz	TV 7
CG	186.200	MHz	TV 9
CQ	202.200	MHz	TV 11
V	169.445	MHz	-
W	171.845	MHz	-

If TV Channels 7, 9, 11, or 13 are present/occupied, use the following base frequency codes. (All are compatible)

Performance Gear VHF and T Series Code/Frequency "Red Dot Group"			This frequency is in US TV Channel:
CE	182.200	MHz	TV 8
CF	183.600	MHz	TV 8
CL	192.200	MHz	TV 10
CV	208.200	MHz	TV 12
V	169.445	MHz	-
W	171.845	MHz	-