

## Shure VP Wireless (169.445-208.200 MHz) Frequency Compatibility Chart

Shure VP Wireless Systems in the United States are available in 8 frequencies between 176.200 MHz and 208.200 MHz, plus 2 traveling frequencies (169.445 MHz & 171.845 MHz). Up to 6 Shure VP Wireless Systems can be operated simultaneously in a single location. Frequencies within a given broadcast TV channel are compatible. Contact Shure Incorporated if you need additional information or assistance in frequency selection and setup.

If TV Channels 8, 10 or 12 are present/occupied, use the following frequency codes. (All are compatible)			
VP Wireless Code/Frequency			This frequency is in US TV Channel:
<b>CA</b>	176.200	MHz	TV 7
<b>CC</b>	177.600	MHz	TV 7
<b>CG</b>	186.200	MHz	TV 9
<b>CQ</b>	202.200	MHz	TV 11
<b>V</b>	169.445	MHz	-
<b>W</b>	171.845	MHz	-

If TV Channels 7, 9, 11, or 13 are present/occupied, use the following base frequency codes. (All are compatible)			
VP Wireless Code/Frequency			This frequency is in US TV Channel:
<b>CE</b>	182.200	MHz	TV 8
<b>CF</b>	183.600	MHz	TV 8
<b>CL</b>	192.200	MHz	TV 10
<b>CV</b>	208.200	MHz	TV 12
<b>V</b>	169.445	MHz	-
<b>W</b>	171.845	MHz	-